



product details

**L 58 W/865**

Product description: L 58 W/865  
Product code: 4050300517940  
Quantity: Shipping carton box (VS) contains  
25 Piece (PCE)

You can find this product in the eCatalog:

[http://catalog.myosram.com?~language=EN&~country=DE&it\\_p=4050300517940](http://catalog.myosram.com?~language=EN&~country=DE&it_p=4050300517940)

Applications	
Suitable for indoor	Yes
Categorizations	
SEG number	8329122
Certificates & Standards	
EEL - Energy Label	A
General Description	
Base (standard designation)	G13
Recycling	Yes
Rated lamp mercury content	4.5 mg
Technical - Electrical Data	
Nominal wattage (packaging)	58 W
Construction wattage	58 W
Rated lamp efficacy (HF data)	Under clarification by authority and standardization body
Technical - Geometries	
Tube diameter	26 mm
Diameter	26.00 mm
Length	1500.00 mm
Length with base excl. base pins/connect	1500 mm
Technical - Lifespan	
Lifespan	20000 h <sup>1)</sup>
Service life	18000 h <sup>2)</sup>
Operation mode LLMF/LSF	50 Hz
Technical - Light Technical Data	
Luminous flux at 25 °C	5000 lm
Luminous flux	5000 lm
Light color	865
Rated color temperature	6500 K
Color rendering index Ra	80...89
Light color as per EN 12464-1	LUMILUX Cool Daylight
Technical - Temperatures	
Rated ambient temp.w.max.luminous flux	25.0 °C



Packaging units				
Product code	Packaging type and content	Dimensions in h x w x l	Gross weight	Volume
4050300517933	Sleeves contains 1 Piece	33,000 mm x 30,000 mm x 1.515,000 mm	242,000 g (0,000 g)	1,500 Cubic dec.
4050300517940	Shipping carton box contains 25 Piece	145,000 mm x 142,000 mm x 1.368,000 mm	6.520,000 g (0,000 g)	31,750 Cubic dec.

Fluorescent lamps in LUMILUX and BASIC light colors offer up to 10 % energy savings compared with previous fluorescent lamps with a 38 mm tube diameter. They are designed to operate with conventional control gear and starters or with QUICKTRONIC electronic control gear. If used in starter circuits, these lamps can operate with standard control gear and recommended compensation capacitors.

For more information go to [www.osram.com/system-guarantee](http://www.osram.com/system-guarantee), [www.osram.com/QUICKTRONIC](http://www.osram.com/QUICKTRONIC)

1) With preheat ECG

2) With preheat ECG